



## **ARGUS USN90-UCB – Serial with 10 tips. The cheap alternative to your original adapter!**

You can supply most of the common Notebooks fast and efficient with the universal adapter **ARGUS USN90-UCB**.

Almost every model can be connected (further adapters are optional available) due to the 10 included, changeable tips. With its flat design, the adapter fits in almost every Notebook bag.

The most important feature is the automatic voltage change. If chosen the right tip, the adapter changes the voltage automatically depending on the tip. A wrong voltage should be almost impossible.

Additionally the **ARGUS USN90-UCB** is equipped with an USB-port to charge USB devices like Smartphones or Tablets.

The efficiency of more than 83% has a positive impact on your wallet and protects the environment.

## Specifications

|                           |   |
|---------------------------|---|
| Output                    | 15-20V, max. 6A, max. 90W   |
| Input                     | 90-264V / 47-63Hz   |
| Number of Tips            | 10  |
| Safeties                  | Over-Voltage-Protection<br>Over-Current-Protection  |
| Device Dimension (h/w/d)  | 18/70/114mm   |
| Package Dimension (h/w/d) | 235/145/50mm  |
| Weight (Net.)             | 175g  |
| Weight (Gros.)            | 485g  |
| Packing Unit              | 1/20/600  |
| Guarantee and Warranty    | 24 Months Guarantee   |
| Article Number            | 88882137  |
| EAN-Code                  | 4260133128477   |
| Scope of Delivery         | Connection Cable<br>Power Cord<br>10 Various Tips<br>Manual<br>(German)   |
| Features                  | Automatic voltage change, depending on Tip<br>USB-Port for charging external USB devices<br>Flat and elegant design<br>Up to 20 Tips optional<br>Housing made of ABS<br>High efficiency > 83% |

### Overview available and included Tips (● = included ; / = available)

| Tip | Voltage | Dimensions in mm | Compatible with  | included/<br>optional | Article No. |
|-----|---------|------------------|--|-----------------------|-------------|
| M1  | 15V     | 6.3 x 3.0 x 12   | Toshiba, NEC   | ●                     | on request  |
| M2  | 16V     | 5.5 x 2.5 x 12   | IBM / Lenovo   | /                     | on request  |
| M3  | 16V     | 6.5 x 4.4 x 10   | Fujitsu, Sony  | /                     | on request  |
| M4  | 18.5V   | 4.8 x 1.7 x 12   | HP / Compaq  | ●                     | on request  |
| M4B | 19V     | 8.0 x 1.7 x 12   | HP / Compaq  | /                     | 88885326    |
| M5  | 19V     | 5.5 x 2.5 x 12   | Acer, Asus, Delta, Gateway, IBM, NEC, Toshiba, Hasee, Lenovo, LiteOn | ●                     | on request  |
| M6  | 19V     | 5.5 x 3.0 x 12   | Samsung  | /                     | on request  |
| M7  | 19V     | 5.5 x 2.1 x 12   | Acer, LiteOn, NEC  | ●                     | on request  |
| M8  | 19.5V   | 6.5 x 4.4 x 10   | Sony   | ●                     | on request  |
| M9  | 19.5V   | 7.4 x 5.0 x 12   | Dell   | /                     | 88885327    |
| M10 | 20V     | 3 holes          | Dell   | /                     | 88885328    |
| M11 | 20V     | 7.9 x 5.4 x 12   | IBM / Lenovo   | ●                     | 88885329    |
| M12 | 18.5V   | 7.4 x 5.0 x 12   | HP / Compaq  | ●                     | 88885331    |
| M14 | 18.5V   | Oval             | HP / Compaq  | /                     | 88885332    |
| M15 | 19V     | 5.5 x 1.7 x 12   | Acer, LiteOn   | ●                     | 88885333    |
| M19 | 19V     | 2.5 x 0.7 x 10   | Asus   | /                     | 88885334    |
| M20 | 19V     | 4.0 x 1.7 x 12   | HP   | /                     | 88885335    |
| M21 | 19.5V   | Octagonal        | Dell   | /                     | 88885336    |
| M22 | 19V     | 3.0 x 1.0 x 10   | Samsung  | /                     | 88885337    |
| M23 | 19.5V   | 4.5 x 3.0 x 10   | Dell   | /                     | 88885338    |
| M24 | 19.5V   | 4.0 x 1.7 x 12   | HP   | /                     | 88885342    |
| M25 | 20V     | 5.5 x 2.5 x 12   | Lenovo   | ●                     | 88885343    |
| M26 | 19V     | 4.0 x 1.35 x 10  | Asus   | /                     | 88885344    |
| M27 | 19V     | 4.5 x 3.0 x 10   | Asus   | /                     | 88885345    |
| M28 | 20V     | 11 x 4.5 x 11    | Lenovo   | ●                     | 88885346    |
| M29 | 19.5V   | 4.5 x 3.0 x 12   | HP Envoy   | /                     | 88885347    |
| M30 | 19.5V   | 4.8 x 14.7 x 10  | HP Envoy   | /                     | 88885348    |