



# 24 Port Fast Ethernet Switch

## ST3124P

 **Highlights** Green Power, Flow Control

 **Features**

- 24 10/100Mbps RJ45 ports
- Supports MAC address self-learning and auto MDI/MDIX
- Green Ethernet technology link down power saving and link on various cable length power saving
- Supports Jumbo frame
- Supports 8K MAC address table
- 4.8 Gbps Switching Capacity
- Fanless design to make sure it works quietly without disturbing your family
- Plug and play, no configuration required



 **Brief**

The netis ST3124P Fast Ethernet Rackmount Switch provides 24 10/100Mbps Auto-Negotiation RJ45 ports .It is ideal for the small and medium office use. All ports support Auto MDI/MDIX function, eliminating the need for crossover cables or uplink ports. The 24 Port Fast Ethernet Rackmount Switch provides you with high-performance, seamless and standard upgrade to improve your old network to a 100Mbps network. It will boost your network performance up to full duplex data transfer.

## Specification:

Hardware	
<b>Interface</b>	24 * 10/100Mbps RJ45 port, Auto-Negotiation, Auto MDI/MDIX
<b>LED</b>	PWR, 1X-24X
<b>Power Supply</b>	DC 12V/1A(Output)
<b>Dimensions (L x W x H )</b>	310 x 200 x 70 mm

Switching Features	
<b>Standard</b>	IEEE 802.3 10Base-T, IEEE 802.3u 100Base-TX, IEEE 802.3x Flow Control, IEEE 802.3az
<b>Access Method</b>	CSMA/CD
<b>Transmission Method</b>	Store and Forward
<b>Data Transmission Rate</b>	10/100Mbps(Half-duplex) 20/200Mbps(Full-duplex)
<b>Switching Fabric Capacity</b>	4.8Gbps
<b>Jumbo Frame</b>	2KB
<b>MAC Address Table</b>	8K, auto-learning & auto-aging

Others	
<b>Certification</b>	FCC, CE
<b>Environment</b>	Operating Temperature: 0°C~40°C Storage Temperature: -20°C~70°C Operating Humidity: 5%~90% non-condensing Storage Humidity: 5%~90% non-condensing
<b>Package</b>	1 * ST3124P 1 * Quick Installation Guide 1 * Power Adapter

Specifications are subject to change without notice. Netis is a registered trademark of Netis Systems Co., Ltd. Other brands and product names are trademarks or registered trademarks of their respective holders. No part of the specifications may be reproduced in any form or by any means or used to make any derivative such as translation, transformation, or adaptation without permission from Netis