

PDU Control C-81



PDU Control C-81

The **PDU** (**P**ower **D**istribution **U**nit) **Control C-81** is the base unit of one system to monitor the remote M-1681 through web interface or SNMP. With enclosed mounting kit it can be mounted into a 19" server cabinet.

The PDU **Control C-81** has 8 outputs for compatible M-1681. Thereby up to 64 sockets can be partially monitored in connection with up to 8x M-1681.

Furthermore, the sensor module Sensor S-1 can be connected to monitor the temperature and the humidity through web interface.

For a functional operation the compatible M-1681 is necessary.



PDU Control C-81

| Specifications | |
|---|---|
| Connectors: | RJ45 10/100Mbps: 1 RJ11 (PDU Bus): 8 RJ11 (Sensor): 1 Power: 1 |
| Controls | Function-Button |
| LED /LED Display | PDU Module Channel Lan Link |
| | Range |
| Power Supply Materials Dimensions (H/W/D) | Power Adapter 1.2mm Steel 44/254/65mm |
| Package Dimension (H/W/D) | 88/505/210mm |
| Weight (net) | 0.73kgs |
| Weight (gross) | 1.49kgs |
| Packing Unit | Shipping Unit: 1 piece |
| Guarantee and Warranty | Case 24 Months Warranty |
| Article Number EAN-Code | 88887072 4260133125308 |
| Scope of Delivery | 4200135125508 Mounting Kit |
| Scope of Delivery | Power Adapter |
| | 8x PDU Bus Cable (2.4m) |
| | "PDU Utility", German and English User Manual on CD |
| Features | Compatible with: PDU Module M-1681 and PDU Sensor S-1 Web Interface |
| | HTTP, HTTPS, SNMP, DHCP, UDP |
| | Current, Measurement of Voltage and |
| | Output |
| | Adjustable Alarm Function |
| | Optional: Sensor to measure temperature and humidity (Article: 88887077) |

